

SM5 Signal Mixer

Hardware Reference



Updated 2024-02-05

© 2016-2024 Tucker-Davis Technologies, Inc. (TDT). All rights reserved.

Tucker-Davis Technologies
11930 Research Circle
Alachua, FL 32615 USA
Phone: +1.386.462.9622
Fax: +1.386.462.5365

Notices

The information contained in this document is provided "as is," and is subject to being changed, without notice. TDT shall not be liable for errors or damages in connection with the furnishing, use, or performance of this document or of any information contained herein.

The latest versions of TDT documents are always online at <https://www.tdt.com/docs/>

Table of Contents

SM5 Signal Mixer

SM5 Overview	4
Power	4
SM5 Features	4
Inputs	4
Clipping	5
SM5 Technical Specifications	5
SM5 Frequency Response	5
SM5 Total Harmonic Distortion	6

SM5 Signal Mixer



SM5 Overview

The SM5 is a three-channel signal mixer. The relative contribution of the three inputs to the final output can be adjusted using a variable gain for two of the inputs. In addition, the signal on the two adjustable channels can be inverted before addition. The input signal range is ± 10 V for each channel, with the additional caveat that the amplified signal for each channel may not exceed ± 10 V without clipping. The range for the summed output is ± 10 V.

Power

The SM5 Signal Mixer is powered via the System 3 zBus ([ZB1PS](#)). No PC interface is required.

SM5 Features

The SM5 Signal Mixer is a three-channel weighted summer with variable input weighting and channel inverting.

Inputs

Three signals input channels (A, B, and C), with a range up to ± 10 V peak, are accessed through front panel BNC connectors. Input channels A and B are multiplied by a weighted, signed constant, K , before being added to the final output. The weighting range for these two channels is adjustable from -20 dB to +20 dB (i.e. $|K| = 0.1$ to 10) using a GAIN knob on the front panel. The sign of K for channels A and B can also be selected using front panel toggle switches, labeled INV-A and INV-B.

If an input is not being used, it should be grounded by attaching a shorted BNC cable. This will prevent unwanted noise from being added to the output.


Clipping

The variable weighting provides a great deal of flexibility in input and output signals. However, care should be taken to avoid clipping any signal component. The SM5 output signal = $(K_a \cdot A) + (K_b \cdot B) + C$ is limited to ± 10 V peak. In addition, the raw inputs, A, B, and C, as well as the weighted inputs, $K_a \cdot A$, and $K_b \cdot B$, are limited to ± 10 V peak.

SM5 Technical Specifications

Input Signal Range	± 10 V peak
Weighting Range	-20.0 to +20.0 dB
Max Output	± 10 V
Spectral Variation	<0.1 dB from 10 Hz to 200 kHz
S/N (typical)	111 dB (20 Hz to 80 kHz)
THD	<0.002% (1 kHz tone ± 7 V peak)
Noise Floor	19 μ Vrms
Output Impedance	20 Ohm
Input Impedance	10 kOhm
Inversion	Channels A & B

SM5 Frequency Response



SM5 Total Harmonic Distortion

